

Black Box Perm Light Plot.lw6

Ch	Purpose	Pos	U#	Instrument Type & Accessory & Load	Clr & Gbo	Addr
1	Shin SR I	Boom 1 SR	1	Source 4 50deg 750w		83
2	Shin SR II	Boom 2 SR	1	Source 4 50deg 750w		133
3	Shin SR III	Boom 3 SR	1	Source 4 50deg 750w		168
4	Shin SR IV	Boom 4 SR	1	Source 4 50deg 750w		184
5	Shin SL I	Boom 1 SL	1	Source 4 50deg 750w		56
6	Shin SL II	Boom 2 SL	1	Source 4 50deg 750w		113
7	Shin SL III	Boom 3 SL	1	Source 4 50deg 750w		140
8	Shin SL IV	Boom 4 SL	1	Source 4 50deg 750w		143
11	Pipe End SR I	G	4	Source 4 Zoom 25°-50° 750w		104
	"	"	5	"		"
	"	"	6	"		"
12	Pipe End SR II	H	10	Source 4 Zoom 25°-50° 750w		108
	"	"	12	"		"
	"	"	13	"		"
13	Pipe End SR III	J	10	Source 4 Zoom 25°-50° 750w		165
	"	"	12	"		"
	"	"	13	"		"
14	Pipe End SR IV	K 8	1	Source 4 Zoom 25°-50° 750w		190
	"	L 9	2	"		"
	"	K 9	"	"		"
15	Pipe End SL I	G	1	Source 4 Zoom 25°-50° 750w		86
	"	"	2	"		"
	"	"	3	"		"

Black Box Perm Light Plot.lw6

Ch	Purpose	Pos	U#	Instrument Type & Accessory & Load	Clr & Gbo	Addr
16	Pipe End SL II	H	1	Source 4 Zoom 25°-50° 750w		90
	"	"	2	"		"
	"	"	4	"		"
17	Pipe End SL III	J	1	Source 4 Zoom 25°-50° 750w		120
	"	"	2	"		"
	"	"	4	"		"
18	Pipe End SL IV	K 2	1	Source 4 Zoom 25°-50° 750w		172
	"	L 1	"	"		"
	"	K 1	2	"		"
21	Backlight DS	H	9	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		130
	"	"	11	"		132
22	Backlight DS	H	8	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		101
23	Backlight DS	H	7	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		124
24	Backlight DS	H	6	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		94
25	Backlight DS	H	3	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		118
	"	"	5	"		95
26	Backlight C	J	9	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		158
	"	"	11	"		103
27	Backlight C	J	8	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		158
28	Backlight C	J	7	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		125
29	Backlight C	J	6	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		147

Black Box Perm Light Plot.lw6

Ch	Purpose	Pos	U#	Instrument Type & Accessory & Load	Clr & Gbo	Addr
30	Backlight C	J	3	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		145
	"	"	5	"		"
31	Backlight US	K 8	2	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		191
	"	K 7	1	"		"
32	Backlight US	K 6	1	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		186
33	Backlight US	K 5	1	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		179
34	Backlight US	K 4	1	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		177
35	Backlight US	K 2	2	6" Fresnel Altman+7.5 4 Leaf Barn Door 1kW		174
	"	K 3	1	"		"
41	Front DS	EF 8	1	6" Fresnel Strand 1kW		74
42	Front DS	EF 6	1	6" Fresnel Strand 1kW		73
43	Front DS	EF 4	1	6" Fresnel Strand 1kW		61
44	Front DS	EF 2	1	6" Fresnel Strand 1kW		62
45	Front C		1	6" Fresnel Strand 1kW		103
46	Front C		1	6" Fresnel Strand 1kW		97
47	Front C		1	6" Fresnel Strand 1kW		91
48	Front C		1	6" Fresnel Strand 1kW		85
49	Front US	IJ 8	1	6" Fresnel Strand+7.5 4 Leaf Barn Door 1kW		134
50	Front US	IJ 6	1	6" Fresnel Strand+7.5 4 Leaf Barn Door 1kW		127
51	Front US	IJ 4	1	6" Fresnel Strand+7.5 4 Leaf Barn Door 1kW		121
52	Front US	IJ 2	1	6" Fresnel Strand+7.5 4 Leaf Barn Door 1kW		115